

Industry

renata
batteries

Scope of supply
Programme de livraison
Lieferprogramm

Batteries for watches, hearing aids and calculators
Piles pour montres, appareils auditifs et calculatrices
Batterien für Uhren, Hörgeräte und Taschenrechner

| Chemical System Système chimique Chemisches System | Dimensions Dimensions Dimensionen | RENATA No. | | Capacity Capacité Kapazität |
|--|--|-------------|---------|-----------------------------------|
| Silver oxide (low drain) 1.55 V Oxyde d'argent (low drain) 1.55 V Silberoxyd (low drain) 1.55 V    +  +  | 4.8×1.6 mm | 337 | SR416SW | 8 mAh |
| | 5.8×1.2 mm | 335 | SR512SW | 6 mAh |
| | 5.8×1.6 mm | 317 | SR516SW | 10.5 mAh |
| | 5.8×2.1 mm | 379 | SR521SW | 16 mAh |
| | 5.8×2.7 mm | 319 | SR527SW | 21 mAh |
| | 6.8×1.4 mm | 339 | SR614SW | 11 mAh |
| | 6.8×1.6 mm | 321 | SR616SW | 14.5 mAh |
| | 6.8×2.1 mm | 364 | SR621SW | 20 mAh |
| | 6.8×2.6 mm | 377 | SR626SW | 28 mAh |
| | 7.9×1.2 mm | 346 | SR712SW | 9.5 mAh |
| | 7.9×1.4 mm | 341 | SR714SW | 15 mAh |
| | 7.9×1.6 mm | 315 | SR716SW | 23 mAh |
| | 7.9×2.1 mm | 362 | SR721SW | 24 mAh |
| | 7.9×2.6 mm | 397 | SR726SW | 32 mAh |
| | 7.9×3.1 mm | 329 | SR731SW | 37 mAh |
| | 7.9×3.6 mm | 384 | SR41SW | 45 mAh |
| | 7.9×5.4 mm | 309 | SR754SW | 80 mAh |
| | 9.5×1.6 mm | 373 | SR916SW | 29 mAh |
| | 9.5×2.0 mm | 371 | SR920SW | 40 mAh |
| | 9.5×2.7 mm | 395 | SR927SW | 55 mAh |
| 9.5×3.6 mm | 394 | SR936SW | 84 mAh | |
| 11.6×1.6 mm | 366 | SR1116SW | 47 mAh | |
| 11.6×2.1 mm | 381 | SR1120SW | 50 mAh | |
| 11.6×3.1 mm | 390 | SR1130SW | 60 mAh | |
| 11.6×3.6 mm | 344 | SR1136SW | 105 mAh | |
| 11.6×4.2 mm | 301 | SR43SW | 130 mAh | |
| 11.6×5.4 mm | 303 | SR44SW | 175 mAh | |
| Silver oxide (high drain) 1.55 V Oxyde d'argent (high drain) 1.55 V Silberoxyd (high drain) 1.55 V   +   +    | 6.8×2.6 mm | 376 | SR626W | 27 mAh |
| | 7.9×2.1 mm | 361 | SR721W | 24 mAh |
| | 7.9×2.6 mm | 396 | SR726W | 32 mAh |
| | 7.9×3.6 mm | 392 | SR41W | 45 mAh |
| | 7.9×5.4 mm | 393 | SR754W | 80 mAh |
| | 9.5×2.0 mm | 370 | SR920W | 40 mAh |
| | 9.5×2.7 mm | 399 | SR927W | 55 mAh |
| | 9.5×3.6 mm | 380 | SR936W | 82 mAh |
| | 11.6×1.6 mm | 365 | SR1116W | 47 mAh |
| | 11.6×2.1 mm | 391 | SR1120W | 50 mAh |
| | 11.6×3.1 mm | 389 | SR1130W | 80 mAh |
| | 11.6×3.6 mm | 350 | | 105 mAh |
| | 11.6×4.2 mm | 386 | SR43W | 130 mAh |
| | 11.6×5.4 mm | 357 | SR44W | 190 mAh |
| | Alkaline 1.5 V Lithium 3 V    | 11.6×5.4 mm | LR44 | |
| 10.0×2.5 mm | | CR1025 | | 30 mAh |
| 12.5×1.6 mm | | CR1216 | | 30 mAh |
| 12.5×2.0 mm | | CR1220 | | 40 mAh |
| 12.5×2.5 mm | | CR1225 | | 48 mAh |
| 16.0×1.6 mm | | CR1616 | | 50 mAh |
| 16.0×2.0 mm | | CR1620 | | 68 mAh |
| 16.0×3.2 mm | | CR1632 | | 137 mAh |
| 20.0×1.6 mm | | CR2016 | | 90 mAh |
| 20.0×2.5 mm | | CR2025 | | 165 mAh |
| 20.0×3.2 mm | | CR2032 | | 225 mAh |
| 23.0×2.0 mm | | CR2320 | | 150 mAh |
| 23.0×2.5 mm | | CR2325 | | 190 mAh |
| 24.5×3.0 mm | | CR2430 | | 285 mAh |
| 24.5×5.0 mm | CR2450N | | 540 mAh | |
| 24.5×7.7 mm | CR2477N | | 950 mAh | |
| Lithium 3 V Rechargeable Zinc air, 1.45 V Zinc air, 1.45 V Zink-Luft, 1.45 V    | 20.0×1.6 mm | LMR2016 | | 25 mAh |
| | 5.8×3.6 mm | 10 | PR70 | 105 mAh |
| | 7.9×3.6 mm | 312 | PR41 | 165 mAh |
| | 7.9×5.4 mm | 13 | PR48 | 305 mAh |
| | 11.6×5.4 mm | 675 | PR44 | 660 mAh |

Cross Reference Guide

Interchangeabilités
Austauschbarkeit

renata
batteries

| renata | ENERGIZER EVEREADY | MAXELL PANASONIC SONY TOSHIBA | VARTA | RAYOVAC | DURACELL | TIMEX | CITIZEN | SEIKO | I.E.C. 60086-3 (60086-2) |
|---------|-----------------------|--|--------|-----------|-----------|-------|-------------|----------|--------------------------------|
| 301 | 301 | SR43SW | V301 | 301 | D 301/386 | D | 280-01 | SB-A8 | SR1142 (SR43) |
| 303 | 303 | SR44SW | V303 | 303 | D 303/357 | A | 280-08 | SB-A9 | SR1154 (SR44) |
| 309 | 309 | SR754SW | V309 | 309 | D 309/393 | | | | SR754 (SR48) |
| 315 | 315 | SR716SW | V315 | 315 | | HA | 280-56 | SB-AT | SR716 (SR67) |
| 317 | 317 | SR516SW | V317 | 317 | | CA | 280-58 | SB-AR | SR516 (SR62) |
| 319 | 319 | SR527SW | V319 | 319 | D 319 | | 280-60 | SB-AE/DE | SR527 (SR64) |
| 321 | 321 | SR616SW | V321 | 321 | | DA | 280-73 | SB-AF/DF | SR616 (SR65) |
| 329 | 329 | SR731SW | V329 | 329 | | | | | SR731 |
| 335 | 335 | SR512SW | V335 | 335 | | | 280-68 | SB-AB | SR512 |
| 337 | 337 | SR416SW | | 337 | | | | | SR416 |
| 339 | 339 | SR614SW | V339 | | | | | | SR614 |
| 341 | 341 | SR714SW | V341 | 341 | | | | | SR714 |
| 344 | 344 | SR1136SW | V344 | 344 | | | | | SR1136 (SR42) |
| 346 | 346 | SR712SW | V346 | 346 | | | 280-66 | SB-DH | SR712 |
| 350 | 350 | | V350 | | | | | | SR1136 (SR42) |
| 357 | 357 | SR44W | V357 | 357 | D 303/357 | J | 280-62 | SB-B9 | SR1154 (SR44) |
| 361 | 361 | SR721W | V361 | 361 | D 361/362 | X | 280-53 | SB-BK/EK | SR721 (SR58) |
| 362 | 362 | SR721SW | V362 | 362 | D 361/362 | S | 280-29 | SB-AK/DK | SR721 (SR58) |
| 364 | 364 | SR621SW | V364 | 364 | D 364 | T | 280-34 | SB-AG/DG | SR621 (SR60) |
| 365 | 365 | SR1116W | | | | | | | SR1116 |
| 366 | 366 | SR1116SW | V366 | 366 | | | 280-46 | | SR1116 |
| 370 | 370 | SR920W | V370 | 370 | D 370/371 | Z | 280-51 | SB-BN | SR921 (SR69) |
| 371 | 371 | SR920SW | V371 | 371 | D 370/371 | | 280-31 | SB-AN | SR921 (SR69) |
| 373 | 373 | SR916SW | V373 | 373 | | WA | 280-45 | SB-AJ/DJ | SR916 (SR68) |
| 376 | 376 | SR626W | | 376 | D 376 | | MA | | SR626 (SR66) |
| 377 | 377 | SR626SW | V377 | 377 | D 377 | BA | 280-39 | SB-AW | SR626 (SR66) |
| 379 | 379 | SR521SW | V379 | 379 | D 379 | JA | 280-59 | SB-AC/DC | SR521 (SR63) |
| 380 | | SR936W | | | | | | | SR936 |
| 381 | 381 | SR1120SW | V381 | 381 | D 381/391 | | 280-27 | SB-AS/DS | SR1121 (SR55) |
| 384 | 384 | SR41SW | V384 | 384 | D 384/392 | | 280-18 | SB-A1/D1 | SR736 (SR41) |
| 386 | 386 | SR43W | V386 | 386 | D 301/386 | H | 280-41 | SB-B8 | SR1142 (SR43) |
| 389 | 389 | SR1130W | V389 | 389 | D 389/390 | M | 280-15 | SB-BU | SR1130 (SR54) |
| 390 | 390 | SR1130SW | V390 | 390 | D 389/390 | | 280-24 | SB-AU | SR1130 (SR54) |
| 391 | 391 | SR1120W | V391 | 391 | D 381/391 | L | 280-30 | SB-BS/ES | SR1121 (SR55) |
| 392 | 392 | SR41W | V392 | 392 | D 384/392 | K | 280-13 | SB-B1 | SR736 (SR41) |
| 393 | 393 | SR754W | V393 | 393 | D 309/393 | F | | SB-B3 | SR754 (SR48) |
| 394 | 394 | SR936SW | V394 | 394 | D 394 | | 280-17 | SB-A4 | SR936 |
| 395 | 395 | SR927SW | V395 | 395 | D 395/399 | LA | 280-48 | SB-AP/DP | SR927 (SR57) |
| 396 | 396 | SR726W | V396 | 396 | D 396/397 | V | 280-52 | SB-BL | SR726 (SR59) |
| 397 | 397 | SR726SW | V397 | 397 | D 396/397 | N | 280-28 | SB-AL | SR726 (SR59) |
| 399 | 399 | SR927W | V399 | 399 | D 395/399 | W | 280-44 | SB-BP/EP | SR927 (SR57) |
| LR44 | A76 | LR44 | V13GA | RW82 | LR44 | KA | 280-904 | SB-F9 | LR1154 (LR44) |
| CR1025 | CR1025 | CR1025 | | | | | | | CR1025 |
| CR1216 | CR/BR1216 | CR/BR1216 | CR1216 | BR1216 | | | | | CR1216 |
| CR1220 | CR1220 | CR/BR1220 | CR1220 | CR1220 | DL1220 | PA | | SB-T13 | CR1220 |
| CR1225 | CR/BR1225 | BR1225 | | BR1225 | | | | | BR1225 |
| CR1616 | CR/BR1616 | CR/BR1616 | CR1616 | BR1616 | DL1616 | YA | 280-209 | | CR1616 |
| CR1620 | CR1620 | CR1620 | CR1620 | CR1620 | DL1620 | EA | 280-208 | | CR1620 |
| CR1632 | | CR1632 | | | | | | | CR1632 |
| CR2016 | CR/BR2016 | CR/BR2016 | CR2016 | CR/BR2016 | DL2016 | FA | 280-202/4/6 | SB-T11 | CR/BR2016 |
| CR2025 | CR2025 | CR2025 | CR2025 | CR2025 | DL2025 | NA | 280-205 | SB-T14 | CR2025 |
| CR2032 | CR/BR2032 | CR/BR2032 | CR2032 | CR2032 | DL2032 | | | SB-T15 | CR2032 |
| CR2320 | BR2320 | CR/BR2320 | CR2320 | BR2320 | | | 280-201 | | CR/BR2320 |
| CR2325 | BR2325 | BR2325 | | BR2325 | | | | SB-T12 | BR2325 |
| CR2430 | CR2430 | CR2430 | CR2430 | CR2430 | DL2430 | | | | CR2430 |
| CR2450N | CR2450 | CR2450 | CR2450 | | DL2450 | | | | CR2450 |
| CR2477N | CR2477 | CR2477 | | | DL2477 | | | | CR2477 |

| renata | RAYOVAC | DURACELL ACTIVAIR | ENERGIZER | ENERGIZER AMPLIFIER | POWER ONE | PANASONIC | TOSHIBA | I.E.C |
|--------|---------|----------------------|-----------|------------------------|-----------|-----------|---------|-------|
| 10 | 10A | DA 10 | AC230E/EZ | AC230 | P10 | PR230H | ZA10 | PR70 |
| 312 | 312A | DA 312 | AC312E/EZ | AC312 | P312 | PR312H | ZA312 | PR41 |
| 13 | 13A | DA 13 | AC13E/EZ | AC13 | P13 | PR13H | ZA13 | PR48 |
| 675 | 675A | DA 675 | AC675E/EZ | AC675 | P675 | PR675H | ZA675 | PR44 |